



This compact, all-in-one Emergency Conversion Kit is suitable for Integral LED Edge-Lit Panels and LED Downlights for use in switchable Maintained mode. It will provide emergency lighting for 3 hours, or optionally for 1.5 hours at a higher output. It is simple to install and features an optional remote test button and LED indicator.

Details

Barcode:	5055788227373
Category:	Emergency
Range Name:	Conversion Kit
Product Type:	Emergency Conversion Kit
Product Body Finish:	Matt white. End cap blue
Market Segment:	Commercial indoor
Finish:	Matt white. End cap blue
Warranty (Years):	3
CE RoHS:	Yes

Physical Data

Product Length (mm):	250
Product Depth (mm):	32
Product Width (mm):	60
Product Weight (g):	300
Optic:	Polycarbonate diffuser
Material:	PVC
Construction:	Injection moulding
Bulb or Luminaire Shape:	Rectangle
Luminaire Fixing:	Surface mounted
Placement / Application:	Indoor, Emergency Lighting

Electrical Data

Input Voltage (V):	220-240
Output Voltage (V):	15-60
Dimming:	Non-Dimmable
Driver Included:	Yes
Electric Current:	AC
Emergency Type:	Non-Maintained

LVD Certified: Yes

Light Data

Lumens Range: 1 to 100

Frequency Range (Hz): 50/60

Environment

LVD Certified: Yes

CE RoHS: Yes

IK Rating (Impact Protection): IK08

IP Rating (Ingress Protection): IP20

Lowest Operating Temperature (°C): 0

Maximum Operating Temperature (°C): 50

Packaging

Package Weight (g): 330

Package Length (mm): 255

Package Width (mm): 63

Package Depth (mm): 35